

SM3500iF





SEMI-SILENT INVERTER GENERATOR

FEATURES

◆ Light: 26 kgs

◆ Compact: 479x340x442mm

◆ Quiet: 68 dBA for Semi-Silent Running

◆ Safe Clean Power: Power Sensitive Electronics

◆ Long Run Time @50 %Load: 10 Hours

◆ Eco Throttle: More Fuel Efficient

◆ Starting Method: Easy Recoil Start

• Stronger Together: Parallel for Double Power

• 50/60Hz: Versatile for Powering Worldwide Electronics

TECHNICAL DATA

MODEL	SM3500iF
Max Starting Power	3500W
Running Power	3200W
AC Load (Volts)	230
Phase, Frequency	Single, 50/60Hz
Rated Amperage	13.9A
Starting Method	Manual
Engine Type	Gasoline
Engine Model/CC/Hp	SH150B/149cc/5.5Hp
Noise Level	68dB
Fuel Tank Capacity	10L
Run Time-50 %Load	10.0Hrs
Run Time-100 %Load	6.0Hrs
Fuel Consumption (50 %Load)	1.0L/Hr
Engine Oil Capacity	0.45L
Digital Display	3-in-1 Meter
Circuit Breaker	1x9A
Remote Control	N/A
Eco-Throttle	\checkmark
Parallel Port	√
Socket	1x16A ,1x30A
DC Port	$\sqrt{}$
THD	<%3
Battery	N/A
Wheel	N/A
Plug	1x30A, DC Plug
Net Weight	26Kg
Gross Weight	30Kg
Packing Dimension(LxWxH)	515x375x480mm
Prodcut Dimension(LxWxH)	479x340x442mm
Q'ty (20GP/40HQ)	264/680



